



Model No.	Detection distance	Operating voltage	Output		Response time	Detection method
			Method	Status		
G70-3A20NA	20-100cm	DC10-30V	NFN	NO	<2mS	Diffusetype
G70-3A20NB	20-100cm	DC10-30V	NFN	NC	<2mS	Diffusetype
G70-3A20NC	20-100cm	DC10-30V	NFN	NO+NC	<2mS	Diffusetype
G70-3A20PA	20-100cm	DC10-30V	FNP	NO	<2mS	Diffusetype
G70-3A20PB	20-100cm	DC10-30V	FNP	NC	<2mS	Diffusetype
G70-3A20PC	20-100cm	DC10-30V	FNP	NO+NC	<2mS	Diffusetype
G70-3B2NA	2m	DC10-30V	NFN	NO	<2mS	Mirrorreflextype
G70-3B2NB	2m	DC10-30V	NFN	NC	<2mS	Mirrorreflextype
G70-3B2NC	2m	DC10-30V	NFN	NO+NC	<2mS	Mirrorreflextype
G70-3B2PA	2m	DC10-30V	FNP	NO	<2mS	Mirrorreflextype
G70-3B2PB	2m	DC10-30V	FNP	NC	<2mS	Mirrorreflextype
G70-3B2PC	2m	DC10-30V	FNP	NO+NC	<2mS	Mirrorreflextype
G70-3C5NA	5m	DC10-30V	NFN	NO	<2mS	Throughbeam
G70-3C5NB	5m	DC10-30V	NFN	NC	<2mS	Throughbeam
G70-3C5NC	5m	DC10-30V	NFN	NO+NC	<2mS	Throughbeam
G70-3C5PA	5m	DC10-30V	FNP	NO	<2mS	Throughbeam
G70-3C5PB	5m	DC10-30V	FNP	NC	<2mS	Throughbeam
G70-3C5PC	5m	DC10-30V	FNP	NO+NC	<2mS	Throughbeam
<hr/>						
G71-3A50NA	50cm	DC10-30V	NFN	NO	<2mS	Diffusetype
G71-3A50NB	50cm	DC10-30V	NFN	NC	<2mS	Diffusetype
G71-3A50NC	50cm	DC10-30V	NFN	NO+NC	<2mS	Diffusetype
G71-3A50PA	50cm	DC10-30V	FNP	NO	<2mS	Diffusetype
G71-3A50PB	50cm	DC10-30V	FNP	NC	<2mS	Diffusetype
G71-3A50PC	50cm	DC10-30V	FNP	NO+NC	<2mS	Diffusetype
G71-3B2NA	2m	DC10-30V	NFN	NO	<2mS	Mirrorreflextype
G71-3B2NB	2m	DC10-30V	NFN	NC	<2mS	Mirrorreflextype
G71-3B2NC	2m	DC10-30V	NFN	NO+NC	<2mS	Mirrorreflextype
G71-3B2PA	2m	DC10-30V	FNP	NO	<2mS	Mirrorreflextype
G71-3B2PB	2m	DC10-30V	FNP	NC	<2mS	Mirrorreflextype
G71-3B2PC	2m	DC10-30V	FNP	NO+NC	<2mS	Mirrorreflextype
G71-3C5NA	5m	DC10-30V	NFN	NO	<2mS	Throughbeam
G71-3C5NB	5m	DC10-30V	NFN	NC	<2mS	Throughbeam
G71-3C5NC	5m	DC10-30V	NFN	NO+NC	<2mS	Throughbeam
G71-3C5PA	5m	DC10-30V	FNP	NO	<2mS	Throughbeam
G71-3C5PB	5m	DC10-30V	FNP	NC	<2mS	Throughbeam
G71-3C5PC	5m	DC10-30V	FNP	NO+NC	<2mS	Throughbeam
<hr/>						
G180-3A10NA	10cm	DC10-30V	NFN	NO	<2mS	Diffusetype
G180-3A10NB	10cm	DC10-30V	NFN	NC	<2mS	Diffusetype
G180-3A10NC	10cm	DC10-30V	NFN	NO+NC	<2mS	Diffusetype
G180-3A10PA	10cm	DC10-30V	FNP	NO	<2mS	Diffusetype
G180-3A10PB	10cm	DC10-30V	FNP	NC	<2mS	Diffusetype
G180-3A10PC	10cm	DC10-30V	FNP	NO+NC	<2mS	Diffusetype
G180-2A10LA	10cm	AC90-250V	SCR	NO	<2mS	Diffusetype
G180-2A10LB	10cm	AC90-250V	SCR	NC	<2mS	Diffusetype
G180-3B2NA	2m	DC10-30V	NFN	NO	<2mS	Mirrorreflextype
G180-3B2NB	2m	DC10-30V	NFN	NC	<2mS	Mirrorreflextype
G180-3B2NC	2m	DC10-30V	NFN	NO+NC	<2mS	Mirrorreflextype
G180-3B2PA	2m	DC10-30V	FNP	NO	<2mS	Mirrorreflextype
G180-3B2PB	2m	DC10-30V	FNP	NC	<2mS	Mirrorreflextype
G180-3B2PC	2m	DC10-30V	FNP	NO+NC	<2mS	Mirrorreflextype
G180-2B2LA	2m	AC90-250V	SCR	NO	<2mS	Mirrorreflextype
G180-2B2LB	2m	AC90-250V	SCR	NC	<2mS	Mirrorreflextype
G180-3C5NA	5m	DC10-30V	NFN	NO	<2mS	Throughbeam
G180-3C5NB	5m	DC10-30V	NFN	NC	<2mS	Throughbeam
G180-3C5NC	5m	DC10-30V	NFN	NO+NC	<2mS	Throughbeam
G180-3C5PA	5m	DC10-30V	FNP	NO	<2mS	Throughbeam
G180-3C5PB	5m	DC10-30V	FNP	NC	<2mS	Throughbeam
G180-3C5PC	5m	DC10-30V	FNP	NO+NC	<2mS	Throughbeam
G180-2C5LA	5m	AC90-250V	SCR	NO	<2mS	Throughbeam
G180-2C5LB	5m	AC90-250V	SCR	NC	<2mS	Throughbeam