

Fusedrawer 3



CAD



Shop pdf-datasheet



GST Accessory for PEM: Fusedrawer for Fuse Links 5x20 mm resp. 6.3x32 mm

[Description](#)
[Electrical Data](#)
[All Variants](#)

Standard or Medical Fuse drawer



Fuse drawer "Fingergrip" with voltage selector
(Fuse links not enclosed)



Fuse drawer "Extrasafe" without voltage selector
(Fuse links not enclosed)



Description

Description

- Component: Snap-in, Rear Mounting
- 2 Functions: Fuseholder for Fuse-links 5x20 mm or 6.3x32 mm, Voltage selector insert
- Approved together with power entry module

Characteristics

- Fuse drawer meets requirements of medical standard IEC/EN 60601-1
- Suitable for use in equipment according to IEC/UL 60950

Other versions on request

- Fuse drawer with other voltage values

References

Fits to type: CD CD-Bowdencable KD KD-Bowdencable KEC KFC

Weblinks

[pdf-datasheet](#), [General Product Information](#), [Approvals](#), [CE declaration of conformity](#), [RoHS](#), [CHINA-RoHS](#), [REACH](#), [Mating Connectors](#), [e-Shop](#), [SCHURTER-Stock-Check](#), [Distributor-Stock-Check](#), [CAD-Drawings](#), [Accessories](#), [Product News](#), [PCS](#), [Detailed request for product](#)

[Top](#)

Electrical Data

Voltage Selector Inserts

Index	Marking on Voltage Selector Insert / Terminal No.				
	KEC	1	2	3	4
	KD	3	4	5	6
4303.2014.00	-	-	-	-	-
4303.2014.01	-	100	120	220	240
4303.2014.02	-	110	150	220	-
4303.2014.03	-	110	-	220	-
4303.2014.04	-	110	220	240	-
4303.2014.05	-	115	-	230	-
4303.2014.06	-	117	220	240	-
4303.2014.08	-	110 V	-	220 V	-
4303.2014.09	-	220	-	240	-
4303.2014.11	-	110	120	220	240

Index "yy" matches the last two characters of the Order Number within the Variants

Index	Marking on Voltage Selector Insert / Terminal No.					
	yy	KEC KD	1 3	2 4	3 5	4 6
4303.2014.12	-	-	115	230	240	-
4303.2014.13	-	-	100	110	220	240
4303.2014.14	-	-	100	117	220	240
4303.2014.15	-	-	100	115	230	-
4303.2014.16	-	-	100	120	230	240
4303.2014.17	-	-	115	120	230	240
4303.2014.19	-	-	220	120	240	230
4303.2014.20	-	-	100	120	230	-
4303.2014.21	-	-	100	-	220	-
4303.2014.22	-	-	100	120	220	230
4303.2014.24	-	-	200	220	240	-
4303.2014.27	-	-	115	200	230	-
4303.2014.32	-	-	100	110	230	240
4303.2014.34	-	-	110	115	230	240
4303.2014.35	-	-	100	115	230	240
4303.2014.36	-	-	100	110	200	230
4303.2014.42	-	-	100	115	120	230
4303.2014.46	-	-	100	120	200	230
4303.2024.00	-	-	-	-	-	-
4303.2024.01	-	-	100	120	220	240
4303.2024.02	-	-	110	150	220	-
4303.2024.03	-	-	110	-	220	-
4303.2024.04	-	-	110	220	240	-
4303.2024.05	-	-	115	-	230	-
4303.2024.06	-	-	117	220	240	-
4303.2024.08	-	-	110 V	-	220 V	-
4303.2024.09	-	-	220	-	240	-
4303.2024.10	-	-	115	220	240	-
4303.2024.11	-	-	110	120	220	240
4303.2024.12	-	-	115	230	240	-
4303.2024.15	-	-	100	115	230	-
4303.2024.16	-	-	100	120	230	240
4303.2024.17	-	-	115	120	230	240
4303.2024.18	-	-	115	-	240	-
4303.2024.19	-	-	220	120	240	230
4303.2024.20	-	-	100	120	230	-
4303.2024.22	-	-	100	120	220	230
4303.2024.25	-	-	120	-	230	-
4303.2024.28	-	-	-	230	240	-
4303.2024.30	-	-	117	220	240	100
4303.2024.31	-	-	117	220	240	100
4303.2024.35	-	-	100	115	230	240
4303.2024.40	-	-	100	110	127	230
4303.2024.44	-	-	100	115	127	230

Index "yy" matches the last two characters of the Order Number within the Variants

Index	Marking on Voltage Selector Insert / Terminal No.					
	yy	KEC KD	1 3	2 4	3 5	4 6
4303.2024.45	-	-	100	115	230	127
4303.2024.46	-	-	100	120	200	230
4303.2036.01	-	-	100	120	220	240
4303.2036.01.1	-	-	100	120	220	240
4303.2036.03	-	-	110	-	220	-
4303.2036.04	-	-	110	220	240	-
4303.2036.05	-	-	115	-	230	-
4303.2036.11	-	-	110	120	220	240
4303.2036.23	-	-	100	110	120	-
4303.2037.01	-	-	100	120	220	240
4303.2037.03	-	-	110	-	220	-
4303.2037.10	-	-	115	220	240	-
4303.2037.13	-	-	100	110	220	240
4303.2114.01	-	-	100	120	220	240
4303.2114.02	-	-	110	150	220	-
4303.2114.03	-	-	110	-	220	-
4303.2114.04	-	-	110	220	240	-
4303.2114.05	-	-	115	-	230	-
4303.2114.08	-	-	110 V	-	220 V	-
4303.2114.09	-	-	220	-	240	-
4303.2114.11	-	-	110	120	220	240
4303.2114.12	-	-	115	230	240	-
4303.2114.13	-	-	100	110	220	240
4303.2114.15	-	-	100	115	230	-
4303.2114.17	-	-	115	120	230	240
4303.2114.20	-	-	100	120	230	-
4303.2114.22	-	-	100	120	220	230
4303.2114.29	-	-	100	117	125	-
4303.2114.43	-	-	115	-	230	-
4303.2114.48	-	-	100	120	208	230
4303.2124.00	-	-	-	-	-	-
4303.2124.01	-	-	100	120	220	240
4303.2124.02	-	-	110	150	220	-
4303.2124.03	-	-	110	-	220	-
4303.2124.04	-	-	110	220	240	-
4303.2124.05	-	-	115	-	230	-
4303.2124.12	-	-	115	230	240	-
4303.2124.15	-	-	100	115	230	-
4303.2124.16	-	-	100	120	230	240
4303.2124.19	-	-	220	120	240	230
4303.2124.22	-	-	100	120	220	230
4303.2124.23	-	-	100	110	120	-
4303.2124.37	-	-	115	230	240	100
4303.2124.39	-	-	220	230	240	-

Index "yy" matches the last two characters of the Order Number within the Variants

Index	Marking on Voltage Selector Insert / Terminal No.				
	KEC	1	2	3	4
yy	KD	3	4	5	6
4303.2401	-	-	-	-	-
4303.2403	-	-	-	-	-
4303.2406	-	-	-	-	-
4303.2408	-	-	-	-	-
4303.2411	-	-	-	-	-
4303.2413	-	-	-	-	-
4303.2416	-	-	-	-	-
4303.2514.01	-	100	120	220	240
4303.2514.02	-	110	150	220	-
4303.2514.03	-	110	-	220	-
4303.2514.05	-	115	-	230	-
4303.2514.08	-	110 V	-	220 V	-
4303.2514.15	-	100	115	230	-
4303.2514.16	-	100	120	230	240
4303.2514.17	-	115	120	230	240
4303.2514.18	-	115	-	240	-
4303.2514.23	-	100	110	120	-
4303.2514.38	-	110	230	220	240
4303.2524.01	-	100	120	220	240
4303.2524.04	-	110	220	240	-
4303.2524.05	-	115	-	230	-
4303.2524.16	-	100	120	230	240
4303.2524.20	-	100	120	230	-
4303.2524.23	-	100	110	120	-
4303.2524.25	-	120	-	230	-
4303.2536.46	-	100	120	200	230
4303.2537.46	-	100	120	200	230
4303.2614.01	-	100	120	220	240
4303.2614.02	-	110	150	220	-
4303.2614.03	-	110	-	220	-
4303.2614.04	-	110	220	240	-
4303.2614.09	-	220	-	240	-
4303.2614.15	-	100	115	230	-
4303.2614.23	-	100	110	120	-
4303.2614.28	-	-	230	240	-
4303.2624.01	-	100	120	220	240
4303.2624.03	-	110	-	220	-
4303.2624.04	-	110	220	240	-
4303.2624.22	-	100	120	220	230
4303.2714.08	-	110 V	-	220 V	-
4303.2737.01	-	100	120	220	240
4303.2737.05	-	115	-	230	-
4303.2737.06	-	117	220	240	-
4303.2901	-	-	-	-	-

Index "yy" matches the last two characters of the Order Number within the Variants

Index	Marking on Voltage Selector Insert / Terminal No.					
	yy	KEC	1	2	3	4
		KD	3	4	5	6
4303.2903	-	-	-	-	-	-
4303.2906	-	-	-	-	-	-
4303.2908	-	-	-	-	-	-
4303.2911	-	-	-	-	-	-
4303.2913	-	-	-	-	-	-

Index "yy" matches the last two characters of the Order Number within the Variants

[Top](#)

All Variants

Table of Variants

Mounting	Fuse-Link	Fuseholder	Comment	Order Number [?]	A=Most Popular [?]
Fingergrip	5 x 20	1-pole	-	4303.2114.01	
Fingergrip	5 x 20	1-pole	-	4303.2114.02	
Fingergrip	5 x 20	1-pole	-	4303.2114.03	
Fingergrip	5 x 20	1-pole	-	4303.2114.04	
Fingergrip	5 x 20	1-pole	-	4303.2114.05	
Fingergrip	5 x 20	1-pole	-	4303.2114.08	
Fingergrip	5 x 20	1-pole	-	4303.2114.09	
Fingergrip	5 x 20	1-pole	-	4303.2114.11	
Fingergrip	5 x 20	1-pole	-	4303.2114.12	
Fingergrip	5 x 20	1-pole	-	4303.2114.15	
Fingergrip	5 x 20	1-pole	-	4303.2114.17	
Fingergrip	5 x 20	1-pole	-	4303.2114.20	
Fingergrip	5 x 20	1-pole	-	4303.2114.22	
Fingergrip	5 x 20	1-pole	-	4303.2114.29	
Fingergrip	5 x 20	1-pole	-	4303.2114.43	
Fingergrip	5 x 20	1-pole	-	4303.2114.48	
Extra-Safe	5 x 20	1-pole	-	4303.2124.00	
Extra-Safe	5 x 20	1-pole	-	4303.2124.01	
Extra-Safe	5 x 20	1-pole	-	4303.2124.03	
Extra-Safe	5 x 20	1-pole	-	4303.2124.04	
Extra-Safe	5 x 20	1-pole	-	4303.2124.05	
Extra-Safe	5 x 20	1-pole	-	4303.2124.12	
Extra-Safe	5 x 20	1-pole	-	4303.2124.15	
Extra-Safe	5 x 20	1-pole	-	4303.2124.19	
Extra-Safe	5 x 20	1-pole	-	4303.2124.22	
Extra-Safe	5 x 20	1-pole	-	4303.2124.23	
Extra-Safe	5 x 20	1-pole	-	4303.2124.37	
Extra-Safe	5 x 20	1-pole	-	4303.2124.39	
Fingergrip	5 x 20	1-pole	-	4303.2406	A
Extra-Safe	5 x 20	1-pole	-	4303.2408	A
Fingergrip	5 x 20	1-pole	spare fuse case	4303.2416	
Fingergrip	5 x 20	2-pole	-	4303.2014.00	A
Fingergrip	5 x 20	2-pole	-	4303.2014.01	A

"yy" see Voltage Selector Inserts Table

Mounting	Fuse-Link	Fuseholder	Comment	Order Number [?]	A=Most Popular [?]
Fingergrip	5 x 20	2-pole	-	4303.2014.02	
Fingergrip	5 x 20	2-pole	-	4303.2014.03	A
Fingergrip	5 x 20	2-pole	-	4303.2014.04	
Fingergrip	5 x 20	2-pole	-	4303.2014.05	A
Fingergrip	5 x 20	2-pole	-	4303.2014.06	
Fingergrip	5 x 20	2-pole	-	4303.2014.08	
Fingergrip	5 x 20	2-pole	-	4303.2014.09	
Fingergrip	5 x 20	2-pole	-	4303.2014.11	
Fingergrip	5 x 20	2-pole	-	4303.2014.12	
Fingergrip	5 x 20	2-pole	-	4303.2014.13	
Fingergrip	5 x 20	2-pole	-	4303.2014.15	
Fingergrip	5 x 20	2-pole	-	4303.2014.16	
Fingergrip	5 x 20	2-pole	-	4303.2014.17	A
Fingergrip	5 x 20	2-pole	-	4303.2014.19	
Fingergrip	5 x 20	2-pole	-	4303.2014.20	
Fingergrip	5 x 20	2-pole	-	4303.2014.21	
Fingergrip	5 x 20	2-pole	-	4303.2014.22	
Fingergrip	5 x 20	2-pole	-	4303.2014.24	
Fingergrip	5 x 20	2-pole	-	4303.2014.27	
Fingergrip	5 x 20	2-pole	-	4303.2014.34	
Fingergrip	5 x 20	2-pole	-	4303.2014.35	
Fingergrip	5 x 20	2-pole	-	4303.2014.36	
Fingergrip	5 x 20	2-pole	-	4303.2014.42	
Extra-Safe	5 x 20	2-pole	-	4303.2024.00	
Extra-Safe	5 x 20	2-pole	-	4303.2024.01	
Extra-Safe	5 x 20	2-pole	-	4303.2024.02	
Extra-Safe	5 x 20	2-pole	-	4303.2024.03	
Extra-Safe	5 x 20	2-pole	-	4303.2024.04	
Extra-Safe	5 x 20	2-pole	-	4303.2024.05	
Extra-Safe	5 x 20	2-pole	-	4303.2024.06	
Extra-Safe	5 x 20	2-pole	-	4303.2024.08	
Extra-Safe	5 x 20	2-pole	-	4303.2024.09	
Extra-Safe	5 x 20	2-pole	-	4303.2024.10	
Extra-Safe	5 x 20	2-pole	-	4303.2024.11	
Extra-Safe	5 x 20	2-pole	-	4303.2024.12	
Extra-Safe	5 x 20	2-pole	-	4303.2024.15	
Extra-Safe	5 x 20	2-pole	-	4303.2024.16	
Extra-Safe	5 x 20	2-pole	-	4303.2024.17	
Extra-Safe	5 x 20	2-pole	-	4303.2024.18	
Extra-Safe	5 x 20	2-pole	-	4303.2024.19	
Extra-Safe	5 x 20	2-pole	-	4303.2024.20	
Extra-Safe	5 x 20	2-pole	-	4303.2024.22	
Extra-Safe	5 x 20	2-pole	-	4303.2024.25	
Extra-Safe	5 x 20	2-pole	-	4303.2024.28	
Extra-Safe	5 x 20	2-pole	-	4303.2024.30	
Extra-Safe	5 x 20	2-pole	-	4303.2024.35	

"yy" see Voltage Selector Inserts Table

Mounting	Fuse-Link	Fuseholder	Comment	Order Number [?]	A=Most Popular [?]
Extra-Safe	5 x 20	2-pole	-	4303.2024.40	
Extra-Safe	5 x 20	2-pole	-	4303.2024.44	
Extra-Safe	5 x 20	2-pole	-	4303.2024.45	
Extra-Safe	5 x 20	2-pole	-	4303.2024.46	
Fingergrip	5 x 20	2-pole	-	4303.2401	A
Extra-Safe	5 x 20	2-pole	-	4303.2403	A
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.01	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.01.1	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.03	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.04	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.05	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.11	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2036.23	
Extra-Safe	5 x 20	2-pole	shorting bar on the neutral side	4303.2037.01	
Extra-Safe	5 x 20	2-pole	shorting bar on the neutral side	4303.2037.03	
Extra-Safe	5 x 20	2-pole	shorting bar on the neutral side	4303.2037.10	
Extra-Safe	5 x 20	2-pole	shorting bar on the neutral side	4303.2037.13	
Fingergrip	5 x 20	2-pole	shorting bar on the neutral side	4303.2411	A
Extra-Safe	5 x 20	2-pole	shorting bar on the neutral side	4303.2413	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.01	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.02	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.03	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.04	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.09	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.23	
Fingergrip	6.3 x 32	1-pole	-	4303.2614.28	
Extra-Safe	6.3 x 32	1-pole	-	4303.2624.01	
Extra-Safe	6.3 x 32	1-pole	-	4303.2624.03	
Extra-Safe	6.3 x 32	1-pole	-	4303.2624.04	
Extra-Safe	6.3 x 32	1-pole	-	4303.2624.22	
Fingergrip	6.3 x 32	1-pole	-	4303.2906	A
Extra-Safe	6.3 x 32	1-pole	-	4303.2908	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.01	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.02	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.03	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.05	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.08	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.15	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.16	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.17	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.18	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.23	
Fingergrip	6.3 x 32	2-pole	-	4303.2514.38	
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.01	
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.04	
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.05	

"yy" see Voltage Selector Inserts Table

Mounting	Fuse-Link	Fuseholder	Comment	Order Number [?]	A=Most Popular [?]
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.16	
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.20	
Extra-Safe	6.3 x 32	2-pole	-	4303.2524.23	
Fingergrip	6.3 x 32	2-pole	-	4303.2901	A
Extra-Safe	6.3 x 32	2-pole	-	4303.2903	A
Fingergrip	6.3 x 32	2-pole	shorting bar on the neutral side	4303.2536.46	
Extra-Safe	6.3 x 32	2-pole	shorting bar on the neutral side	4303.2537.46	
Fingergrip	6.3 x 32	2-pole	shorting bar on the neutral side	4303.2911	
Extra-Safe	6.3 x 32	2-pole	shorting bar on the neutral side	4303.2913	

"yy" see Voltage Selector Inserts Table

[Top](#)

Packaging unit

50 Pcs

The specifications, descriptions and illustrations indicated in this document are based on current information. All content is subject to modifications and amendments. Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability and test each product selected for their own applications.

03.03.2015