


CMR Monolever Switches




Features

- You can smoothly and swiftly handle the lever in four directions upward, rightward, downward, and leftward
- Three alternatives of movement are attainable in each direction: Go-on, auto-return, and blockade-enforcing
- You are free, as you like, to operate in four, three, or two directions with the switch
- Rubber bushing is water-proof, oil-resistant, and dustpreventive



BR-1 BR-2 BR-3

Models Designations



Items	Code	Description
① Type	CMR	Round type
	CMS	Square type
	CMRS	Round type
	CMRN	Seal Round
	CMSN	Seal Square
	CMRSN	Seal Round
② Mounting Hole	30	Φ30m/m only
③ No.of contact Blocks fitted	1~4	1~4
④ Actuating keys	1	Go-on
	2	Auto-return
	0	Blockade-enforcing
⑤ Type of contact Blocks fitted	00	None
	10	1a(1NO)
	20	2a(2NO)
	01	1b(1NC)
	02	2b(2NC)
	11	1a1b(1NO-1NC)

Note: When you place order, please kindly designate clockwise the movement way and type of contact fitted.

Ratings

AC	Rated voltage		110V	220V	440V
	Rated current		10A	6A	3A
	Breaking current capacity		50A	30A	10A
DC	Resistance Load	Rated voltage	110V	220V	600V
		Rated Current	2.2A	1.1A	0.4A
		Breaking Current	2.42A	1.21A	0.44A
	Inductive Load	Rated Current	1.2A	0.45A	0.2A
Breaking Current		1.32A	0.5A	0.22A	

CMR Monolever Switches

Appearance and Dimension

